



RF Cable Assemblies Technical Data Sheet


PE3W02743/HS

Configuration

Connector 1: N MaleConnector 2: BNC MaleCable Type: LMR-195

Features

- Max Frequency 4 GHz
- Shielding Effectivity > 90 dB
- 80% Phase Velocity
- · Double Shielded
- PE Jacket



Applications

· General Purpose

· Laboratory Use

Description

Pasternack's PE3W02743/HS type N male to BNC male cable using LMR-195 coax is part of our full line of RF components available for same-day shipping. Pasternack's flexible RF cable assemblies are ideal for applications where tight bends and flexure are required. This Pasternack type N to BNC cable assembly has a male to male gender configuration with 50 ohm flexible LMR-195 coax. The PE3W02743/HS type N male to BNC male cable assembly operates to 4 GHz. The double shielding of this Pasternack cable assembly provides excellent shielding effectiveness of better than 90 dB.

Custom versions of most RF cable assemblies can be built and shipped same day. Custom cable assembly lengths can be obtained by specifying the desired length on the web site at time of order or by contacting a sales representative. Other available RF cable assembly value added services include connector orientation or clocking, heat shrink booting and custom labeling. RF testing can also be performed to document the electrical performance of your cable assembly.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using LMR-195 Coax with HeatShrink PE3W02743/HS

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451





RF Cable Assemblies Technical Data Sheet

PE3W02743/HS

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		4	GHz
VSWR		/ //	1.5:1	
Velocity of Propagation		80		%
RF Shielding	90			dB
Group Delay		1.27 [4.17]		ns/ft [ns/m]
Capacitance		25.4 [83.33]		pF/ft [pF/m]
Inductance		0.064 [0.21]		uH/ft [uH/m]
DC Resistance Inner Conductor		7.6 [24.93]		Ohms/1000ft [Ohms/
Km]				
DC Resistance Outer Conductor		4.9 [16.08]		Ohms/1000ft [Ohms/
Km]				
Jacket Spark			3,000	Vrms

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	0.25	0.5	1	2.5	4	GHz
Insertion Loss (Max.)	0.05	0.08	0.11	0.19	0.23	dB/ft
	0.16	0.26	0.36	0.62	0.75	dB/m

Electrical Specification Notes:

Insertion Loss does not include the loss of connectors. Insertion Loss is estimated as 0.2dB of connector loss

Mechanical Specifications

Cable Assembly

Diameter 0.81 in [20.57 mm]

Cable

Cable TypeLMR-195Impedance50 OhmsInner Conductor TypeSolidInner Conductor Material and PlatingCopperDielectric TypePE (F)Number of Shields2

Shield Layer 1 Aluminum Tape
Shield Layer 2 Tinned Copper Braid

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using LMR-195 Coax with HeatShrink PE3W02743/HS

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com





RF Cable Assemblies Technical Data Sheet

PE3W02743/HS

Jacket Material

Jacket Diameter

One Time Minimum Bend Radius Repeated Minimum Bend Radius Bending Moment Flat Plate Crush

Tensile Strength

PE, Black

0.195 in [4.95 mm]

0.5 in [12.7 mm] 2 in [50.8 mm] 0.2 lbs-ft [0.27 N-m] 15 lbs/in [0.27 Kg/mm] 40 lbs [18.14 Kg]

Connectors

Connector 1	Connector 2 BNC Male	
N Male		
MIL-STD-348	MIL-STD-348A	
50 Ohms	50 Ohms	
Brass, Gold	Brass, Gold	
ASTM B488	30 µin minimum	
Teflon	PTFE	
Brass, Tri-Metal Brass, N		
	100 μin minimum	
Brass, Tri-Metal	Brass, Nickel	
	100 μin minimum	
13/16 Inch		
	N Male MIL-STD-348 50 Ohms Brass, Gold ASTM B488 Teflon Brass, Tri-Metal Brass, Tri-Metal	

Mechanical Specification Notes:

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using LMR-195 Coax with HeatShrink PE3W02743/HS

^{*}All cable assemblies have a length tolerance of 1.5% or ± 3/8", whichever is greater.





RF Cable Assemblies Technical Data Sheet

PE3W02743/HS

How to Order

Part Number Configuration:

PE3W02743/HS - xx uu

Unit of Measure:
cm = Centimeters

Length
Base Number

Example: PE3W02743/HS-12 = 12 inches long cable PE3W02743/HS-100cm = 100 cm long cable

N Male to BNC Male Cable Using LMR-195 Coax with HeatShrink from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: N Male to BNC Male Cable Using LMR-195 Coax with HeatShrink PE3W02743/HS

URL: https://www.pasternack.com/n-male-bnc-male-lmr195-cable-assembly-pe3w02743-hs-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

PE3W02743/HS CAD Drawing
N Male to BNC Male Cable Using LMR-195 Coax with HeatShrink

