

SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax



RF Cable Assemblies Technical Data Sheet

PE39345H-24

Configuration

Connector 1: SMA FemaleConnector 2: FAKRA PlugCable Type: RG174

Electrical Specifications

Description	Minimum	Typical	Maximum	Units
Frequency Range	DC		1,000	MHz
Velocity of Propagation		66		%
Capacitance		30.8 [101.05]		pF/ft [pF/m]

Specifications by Frequency

Description	F1	F2	F3	F4	F5	Units
Frequency	50	100	250	500	1,000	MHz
Insertion Loss (Typ.)	0.284	0.368	0.474	0.623	0.84	dB

Mechanical Specifications

Cable Assembly

 Length*
 24 in [609.6 mm]

 Diameter
 0.37 in [9.4 mm]

 Weight
 0.037 lbs [16.78 g]

Cable

Cable TypeRG174Impedance50 OhmsInner Conductor TypeStrandedInner Conductor Material and PlatingCopper Clad Steel

Dielectric Type PE (LD)

Number of Shields

Shield Layer 1 Tinned Copper Braid
Jacket Material PVC, Black
Jacket Diameter 0.1 in [2.54 mm]

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax PE39345H-24

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 **Phone:** (866) 727-8376 or (949) 261-1920 • **Fax:** (949) 261-7451

Sales@Pasternack.com • Techsupport@Pasternack.com



SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax



RF Cable Assemblies Technical Data Sheet

PE39345H-24

Connectors

Description	Connector 1	Connector 2 FAKRA Plug	
Туре	SMA Female		
Specification	MIL-STD-348		
Impedance	50 Ohms	50 Ohms	
Configuration	Straight	Straight	
Mating Cycles	100		
Contact Material and Plating	Beryllium Copper, Gold	Phosphor Bronze, Gold	
Dielectric Type	Teflon	Teflon	
Outer Conductor Material and Plating	Brass, Nicke		
Body Material and Plating	Brass, Nickel	Plastic	

Mechanical Specification Notes:

Compliance Certifications (see product page for current document)

Plotted and Other Data

Notes:

Values at 25°C, sea level.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax PE39345H-24

^{*}All cable assemblies have a length tolerance of 1.5% or \pm 3/8", whichever is greater.



SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax



RF Cable Assemblies Technical Data Sheet

PE39345H-24

How to Order



Example: PE39345H-12 = 12 inches long cable

PE39345H-100cm = 100 cm long cable

SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax from Pasternack Enterprises has same day shipment for domestic and International orders. Our RF, microwave and millimeter wave products maintain a 99.4% availability and are part of the broadest selection in the industry.

Click the following link (or enter part number in "SEARCH" on website) to obtain additional part information including price, inventory and certifications: SMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax PE39345H-24

URL: https://www.pasternack.com/sma-female-fakra-plug-rg174au-cable-assembly-pe39345h-24-p.aspx

The information contained in this document is accurate to the best of our knowledge and representative of the part described herein. It may be necessary to make modifications to the part and/or the documentation of the part, in order to implement improvements. Pasternack reserves the right to make such changes as required. Unless otherwise stated, all specifications are nominal. Pasternack does not make any representation or warranty regarding the suitability of the part described herein for any particular purpose, and Pasternack does not assume any liability arising out of the use of any part or documentation.

Pasternack Enterprises, Inc. • P.O. Box 16759, Irvine, CA 92623 Phone: (866) 727-8376 or (949) 261-1920 • Fax: (949) 261-7451 Sales@Pasternack.com • Techsupport@Pasternack.com

PE39345H-24 CAD DrawingSMA Female to Violet FAKRA Plug Cable 24 Inch Length Using RG174 Coax

